

CtG FCN-B-51 amplifier 03/11/10 bom k.b.c.

Quan	Description
1	H1441-26 16" X 8" X 2" STEEL BLACK P=COAT CHASSIS
1	H1431-26 16" X 8" X 2" STEEL BLACK P=COAT BOTTOM
1	H1451-26 16" X 8" X 5.2" STEEL BLACK P=COAT CAGE
6	KNOBS
1	A.C. CORD 16/18 GA
1	A.C. CORD STRAIN RELIEF
1	EYELET FIBER BOARD
2	BRASS PLATES
6	OCTAL SOCKETS
1	LAMP HOLDER AND BEZEL
1	FP CAN CAP HOLDER
16	#4-40 X 3/8" MACHINE SCREW WITH NUT & STAR WASHER
2	FIBER BOARD MOUNTING SCREWS/SPACERS/WASHERS
1	25u 800V CAP HOLDER
	WIRE

Part	Value	Description
V1	6SL7	DUAL TRIODE
V2	6SL7	DUAL TRIODE
V3	6SL7	DUAL TRIODE
V4	6L6GC	POWER TUBE
V5	6L6GC	POWER TUBE
V6	5AR4	RECTIFIER
L1	T-47	LAMP - 150mA
C1	.022u	CAPACITOR 630v
C2	470pF	MICA CAPACITOR 630v
C3	.022u	CAPACITOR 630v
C4	.022u	CAPACITOR 630v
C5	470pF	MICA CAPACITOR 630v
C6	.001u	CAPACITOR 630v
C7	.022u	CAPACITOR 630v
C8	.01u	CAPACITOR 630v
C9	50u 63V	ELECTROLYTIC CAPACITOR
C10	.0047u	CAPACITOR 630v
C11	22u 25V	ELECTROLYTIC CAPACITOR
C12	.022u	CAPACITOR 630v
C13	.022u	CAPACITOR 630v
C14	470pF	MICA CAPACITOR 630v
C15	22u 100V	ELECTROLYTIC CAPACITOR
C16	.022u	CAPACITOR 630v
C17	470pF	MICA CAPACITOR 630v

C18	.001u	CAPACITOR 630v
C19	40u 500V	ELECTROLYTIC CAPACITOR - 1/3 FP CAN
C20	40u 500V	ELECTROLYTIC CAPACITOR - 1/3 FP CAN
C21	40u 500V	ELECTROLYTIC CAPACITOR - 1/3 FP CAN
C22	25u 800V	ELECTROLYTIC CAPACITOR
C23	.01u	CAPACITOR 630v
C24	.0047u	CAPACITOR 630v
C25	100u 100v	ELECTROLYTIC CAPACITOR
D1	1N4007	1A 1000V DIODE
F1	3A SLO BLO	CHASSIS MOUNT FUSE HOLDER
J1	W-SC-12A	1/4" CHASSIS MOUNT PHONE JACK (tip-shunt)
J2	W-SC-12A	1/4" CHASSIS MOUNT PHONE JACK (tip-shunt)
J3	W-SC-11	1/4" CHASSIS MOUNT PHONE JACK (open)
J4	W-SC-12A	1/4" CHASSIS MOUNT PHONE JACK (tip-shunt)
J5	W-SC-12A	1/4" CHASSIS MOUNT PHONE JACK (tip-shunt)
R1	10K	1/2 W CF RESISTOR
R2	120K	1/2 W CF RESISTOR
R3	1K	1/2 W CF RESISTOR
R4	220K	1/2 W CF RESISTOR
R5	270K	1/2 W CF RESISTOR
R6	220	1/2 W CF RESISTOR
R7	120K	1/2 W CF RESISTOR
R8	270K 5%	1/2 W CF RESISTOR
R9	3.3M	1/2 W CF RESISTOR
R10	1M (A)	1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
R11	470K	1/2 W CF RESISTOR
R12	1M (A)	1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
R13	120K	1/2 W CF RESISTOR
R14	1M (A)	1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
R15	500	5 W RESISTOR
R16	5.6K	1/2 W CF RESISTOR
R17	270K	1/2 W CF RESISTOR
R18	2.2K	1/2 W CF RESISTOR
R19	510K	1/2 W CF RESISTOR
R20	470K	1/2 W CF RESISTOR
R21	120K	1/2 W CF RESISTOR
R22	270K 5%	1/2 W CF RESISTOR
R23	220K	1/2 W CF RESISTOR
R24	22K	1/2 W CF RESISTOR
R25	1K	1/2 W CF RESISTOR
R26	1K	1/2 W CF RESISTOR
R27	470K	1/2 W CF RESISTOR
R28	470K	1/2 W CF RESISTOR
R29	470K	1/2 W CF RESISTOR

R30	47K	1/2 W CF RESISTOR
R31	120K	1/2 W CF RESISTOR
R32	1K	10W RESISTOR
R33	220K	1/2 W CF RESISTOR
R34	22K	2W RESISTOR
R35	22K	2W RESISTOR
R36	3.3M	1/2 W CF RESISTOR
R37	1M (A)	1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
R38	270K	1/2 W CF RESISTOR
R39	2.2K	1/2 W CF RESISTOR
R40	1M (A)	1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
R41	120K	1/2 W CF RESISTOR
R42	1M (A)	1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
R43	5.6K	1/2 W CF RESISTOR
R44	270K	1/2 W CF RESISTOR
R45	1K	1/2 W CF RESISTOR
R46	22K	1/2 W CF RESISTOR
R47	10K (L)	POTENTIOMETER-LINEAR TAPER
R48	22K	1/2 W CF RESISTOR
R49	500	5W RESISTOR
S1	SPST	MINI TOGGLE SWITCH
S2	SPDT	1/2" BUSHING -TOGGLE SWITCH - 5A
S4	SPST	MINI TOGGLE SWITCH
S5	SPST	1/2" BUSHING -TOGGLE SWITCH - 5A
S6	SPST	1/2" BUSHING -TOGGLE SWITCH - 5A
S7	SPDT	1/2" BUSHING -TOGGLE SWITCH - 5A
TR1	OT	40W - 6500 (3250) pri 8(4)/16(8)OHM sec OUTPUT TRANSFORMER - OT 215
TR2	PT	360VAC (CT) 200mA POWER TRANSFORMER - W022798