

CtG A-6F5 amplifier 03/18/10 bom k.b.c.

Quan	Description
1	H1441-26 16" X 8" X 2" STEEL BLACK P=COAT CHASSIS
1	H1431-26 16" X 8" X 2" STEEL BLACK P=COAT BOTTOM
1	H1451-26 16" X 8" X 5.2" STEEL BLACK P=COAT CAGE
6	KNOBS
1	A.C. CORD 16/18 GA
1	A.C. CORD STRAIN RELIEF
1	EYELET FIBER BOARD
2	BRASS PLATES
3	OCTAL SOCKETS
3	9 PIN SOCKETS
1	LAMP HOLDER AND BEZEL
1	FP CAN CAP HOLDER
16	#4-40 X 3/8" MACHINE SCREW WITH NUT & STAR WASHER
2	FIBER BOARD MOUNTING SCREWS/SPACERS/WASHERS
1	25u 800V CAP HOLDER
	WIRE

Part	Value	Description
V1	12AY7	DUAL TRIODE
V2	12AX7	DUAL TRIODE
V3	12AX7	DUAL TRIODE
V4	6L6GC	POWER TUBE
V5	6L6GC	POWER TUBE
V6	5AR4	RECTIFIER
LMP	T-47	LAMP - 150mA
C1	250pF	MICA CAPACITOR 630v
C2	.1u	CAPACITOR 630v
C3	.022u	CAPACITOR 630v
C4	.022u	CAPACITOR 630v
C5	100pF	MICA CAPACITOR 630v
C6	.022u	CAPACITOR 630v
C7	.022u	CAPACITOR 630v
C8	.1u	CAPACITOR 630v
C9	250u 6V	ELECTROLY POLARIZED
C10	.1u	CAPACITOR 630v
C11	.1u	CAPACITOR 630v
C12	.022u	CAPACITOR 630v
C13	8u 450V	ELECTROLYTIC CAPACITOR
C14	20u 500V	ELECTROLYTIC CAPACITOR
C15	20u 500V	ELECTROLYTIC CAPACITOR
C16	40u 500V	ELECTROLYTIC CAPACITOR
C17	8u 150V	ELECTROLYTIC CAPACITOR
C18	8u 150V	ELECTROLYTIC CAPACITOR
D1	1N4007	DIODE 1000PIV
F1	3A SLO BLO	FUSE

J1 W-SC-12A 1/4" CHASSIS MOUNT PHONE JACK (tip-shunt)
 J2 W-SC-11 1/4" CHASSIS MOUNT PHONE JACK (open)
 J3 W-SC-12A 1/4" CHASSIS MOUNT PHONE JACK (tip-shunt)
 J4 W-SC-12A 1/4" CHASSIS MOUNT PHONE JACK (tip-shunt)
 J5 W-SC-11 1/4" CHASSIS MOUNT PHONE JACK (open)

L1 14684 CHOKE

R1 27k 1/2 W CC RESISTOR
 R2 56k 1/2 W CC RESISTOR
 R3 250k (L) 1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
 R4 82k 5% 1/2 W CC RESISTOR
 R5 220k 1/2 W CC RESISTOR
 R6 470 2W RESISTOR, American symbol
 R7 1M 1/2 W CC RESISTOR
 R8 100k 1/2 W CC RESISTOR
 R9 100k 1/2 W CC RESISTOR
 R10 10k 1/2 W CC RESISTOR
 R11 470 1/2 W CC RESISTOR
 R12 68k 1/2 W CC RESISTOR
 R13 1M (A) 1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
 R14 1M (A) 1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
 R15 1M 1/2 W CC RESISTOR
 R16 100k 5% 1/2 W CC RESISTOR
 R17 220k 1/2 W CC RESISTOR
 R18 470 2W RESISTOR, American symbol
 R19 270k 1/2 W CC RESISTOR
 R20 820 1/2 W CC RESISTOR
 R21 1M 1/2 W CC RESISTOR
 R22 25k (L) 1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
 R23 15k 1/2 W CC RESISTOR
 R24 270k 1/2 W CC RESISTOR
 R25 100k 1/2 W CC RESISTOR
 R26 5k (L) 1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
 R27 1M (A) 1/2 W / 3/8" BUSHING / 1 /4" SHAFT - 24mm POTENTIOMETER-AUDIO TAPER
 R28 820 1/2 W CC RESISTOR
 R29 100k 1/2 W CC RESISTOR
 R30 1500 1/2 W CC RESISTOR
 R31 68k 1/2 W CC RESISTOR
 R32 15k 1/2 W CC RESISTOR
 R33 56k 1/2 W CC RESISTOR
 R34 10K 2W RESISTOR, American symbol
 R35 4.7K 2W RESISTOR, American symbol
 R36 1M 1/2 W CC RESISTOR

S1 SPST SWITCH
 S2 SPST SWITCH
 S3 WSW-R2x3 SWITCH Rotary

TR1 404248 TRANSFORMER
 TR2 22798 TRANSFORMER